



NOVATEL WIRELESS™

# AT&T Mobile Hotspot

MiFi® 2372

## Quickstart



at&t

## Welcome to AT&T

Thank you for purchasing an AT&T Mobile Hotspot, MiFi 2372.

Please use this Quickstart to get a brief overview of the major features of your new MiFi 2372 and DataConnect service

OR

take advantage of our interactive web tutorials at

**[att.com/Tutorials](http://att.com/Tutorials)**

for the most complete and up-to-date device setup information. The online tutorials include step-by-step instructions and an easy search function to find what you need quickly.

Thanks again for choosing AT&T.


# Getting Started

## Insert the SIM and the Battery

1. Slide open the battery door on the back of the device.
2. Insert the SIM card (if not pre-installed) into the SIM slot as shown.



3. Now, insert the battery, lining up the contact points.



4. Slide the battery door closed.

## Charge the Battery

Connect the A/C charger to the device and charge for a minimum of 4 hours before use. The LED will flash amber while the device is charging and glow solid amber once charging is complete.

# Connecting to the AT&T Mobile Network and Accessing the Internet

Please note that the device is secure. Only users who have the Wi-Fi Password/Key will be able to connect to the Internet with the device. You can find your device SSID and the Wi-Fi Key on the label on the back of the device.



1. Ensure that the device is charged or connected to an electrical outlet.
2. Press the LED power button; the LED light will turn on.
3. A blue Wi-Fi indicator on the front of the device appears when ready to connect.
4. Select the SSID (i.e. MiFi 2372 XXXX) in your computer's Wi-Fi Network Connections list.
5. When prompted for a Password/Key from your Operating System, enter the Wi-Fi Key from the label on the back of the device then click **Connect**.



The blue Wi-Fi light will begin blinking when you have successfully connected your laptop to the MiFi 2372. You are now ready to start using the Internet.

# Access Data Usage and Device Settings

You can access the advanced features of your MiFi 2372 through the Web Interface:

1. Launch your web browser (no Internet connection required).
2. Type **att.mifi** in the address bar and hit enter.\*
3. Use password **attmifi** to log in (in the top right corner of the Web Interface).

The Web Interface allows you to:

- View your data usage, your messages and the wireless device number
- Change your Wi-Fi Password/Key
- Enable GPS on the device



\*Note: Alternatively, you can enter device IP address **http://192.168.1.1**.

# LED Indicators



## Power/Connection LED

CYAN		SMS	Flashing: New or unread message notification
RED		Error	Flashing: Low battery
			Solid: Device error (See Troubleshooting in the web tutorial)
AMBER		Battery	Flashing: Battery charging
			Solid: Battery fully charged
GREEN		GPRS/EDGE	Flashing: GPRS/EDGE service is available
			Solid: Connected to a network using GPRS/EDGE
VIOLET		HSPA	Flashing: HSPA service is available
			Solid: Connected to a network using HSPA
BLUE		UMTS	Flashing: UMTS service is available
			Solid: Connected to a network using UMTS



## Wi-Fi LED

BLUE		Wi-Fi	No Light: Wi-Fi is off or plugged into USB port
			Flashing: On and connected
			Solid: On with no users connected

# Need help?

## On the Web

For more information about using your new device, please refer to the interactive web tutorial available at [att.com/Tutorials](http://att.com/Tutorials). Select Manufacturer: **Novatel Wireless** and Model: **MiFi 2372** from the drop-down menus.

Additional support is available online including device specifications, troubleshooting and user forums at [att.com/DeviceSupport](http://att.com/DeviceSupport).

## On the Phone

Call AT&T Customer Care at 800-331-0500 for assistance with your AT&T service. Please enter the 10-digit wireless phone number associated with your MiFi 2372 when prompted. This will direct your call to a specialized Care team. The wireless phone number associated with your DataConnect rate plan can be found:

- on your sales receipt
- on your monthly statement
- on att.mifi

MiFi, the MiFi logo, Novatel Wireless and the Novatel Wireless logo are either registered trademarks or trademarks of Novatel Wireless, Inc. © 2011 AT&T Intellectual Property. All rights reserved. AT&T, the AT&T logo and all other AT&T marks contained herein are trademarks of AT&T Intellectual Property and/or AT&T affiliated companies. All other marks contained herein are the property of their respective owners.

